


STEREO POWER AMPLIFIER

L-1000M

SERVICE MANUAL

KENWOOD

©1989-12 PRINTED IN JAPAN
B51-4021-11(B)3019




* Refer to parts list on page 16.

L-1000M

DISASSEMBLY FOR REPAIR


1. Detaching Method of Case and Front Panel:

1. Detach 8 pieces of screws (①) of the panels on the both sides.
2. Detach 2 pieces of screws (②) of the upper surface cover.
3. Detach 7 pieces of screws (③) of the control panel.




2. Detaching Method of X13 B/5, C/5, D/5 and E5 (attached units):

1. Detach 9 pieces of screws (④) of each unit.
2. Detach 2 pieces of screws (⑤).
3. Detach 8 pieces of screws (⑥) which are retaining the chassis.
4. Detach 2 pieces of screws (⑦) of the cover.
5. Detach 4 pieces of screws (⑧) of the unit.




3. Detaching Method of X09 (Audio Unit):

1. Turning the main body upside down, detach 12 pieces of screws (⑨) of bottom plate.
(Note: Place the body upright to fit the bottom plate.)
2. Detach 2 pieces of screws (⑩) which are retaining radiating plate to the frame.




DISASSEMBLY FOR REPAIR


- 3. Detach 4 pieces of screws (11) of the cover.
- 4. Detach 6 pieces of screws (12) of the radiator.



- 5. Lift the outer side (side A) of the radiator. At this time, detaching plugs CN5, 7(L) or CN6, 8(R) (13) makes it easier to lift. Then turn the radiator so that the PCB will face inside (14, 15).



- 4. Detaching Method of X13 5/A (attached unit)
Detach 6 pieces of screws (16) of the back panel and detach the unit together with the back panel toward the direction of the arrow mark (17).
- 5. Detaching Method of X07 (main amplifying unit)
Pushing the clicks in the 8 places of the unit holder (18) toward the direction of the arrow mark (19), detach the unit toward the direction of the arrow mark.



ADJUSTMENT

Sequence	Item	Input side setting	Output side setting	Amp setting	Adjusting place	Adjusting method	Figure
Unless otherwise noted, each switch should be set as follows:/ POWER:ON SPEAKER:B REC OUT:OFF Selector:PHONO							
1	Silence current	—	Between CN9 1 and 2 and between CN9 3 and 4/ Between CN10 1 and 2 and between CN10 3 and 4	VOLUME:0	VR3,VR1 VR2,VR4	9mV	(a)


RÉGLAGE

Ordre	Item	Côté entrée Mise en fonctionnement	Côté sortie Mise en fonctionnement	Amplificateur Mise en fonctionnement	Point à régler	Méthode de réglage	Figure
Mettre les interrupteurs correspondants en fonctionnement dans les conditions suivantes, sauf cas spécifié, Puissance:Mise en marche Haut-parleur:B REC OUT:Enregistrement Sélecteur:PHONO							
1	Courant sans signal	—	CN9 Entre 1 et 2, Entre 3 et 4 CN10 Entre 1 et 2, Entre 3 et 4	VOLUME:0	VR3,VR1 VR2,VR4	9mV	(a)

EINSTELLUNGEN



Vorbereitung	Punkt	Einstellung am Eingang	Einstellung am Ausgang	Einstellung am Verstärker	Einstellteil	Einstellverfahren	Diagramm
Falls nicht anders angegeben, die nachstehenden Bedienteile wie folgt einstellen: Netzschalter POWER:ON Lautsprecherschalter SPEAKER:B Tonbandausgang REC OUT:OFF Programmquellenwähler:PHONO							
1	Kein Signalpegel	—	CN 9, zwischen 1 – 2 und zwischen 3 – 4 CN 10, zwischen 1 – 2 und zwischen 3 – 4	Lautstärkereglern VOLUME:0	VR3,VR1 VR2,VR4	9mV	(a)

L-1000M L-1000M





PC BOARD (Component Side View)

MAIN AMPLIFIER UNIT








AUDIO UNIT




Refer to the schematic diagram for the values of resistors and capacitors.

- 1
- 2
- 3
- 4
- 5
- 6
- 7



Refer to the schematic diagram for the values of resistors and capacitors.



2SA1123
2SA1124
2SA1534A
2SA733(A)
2SA992

2SC1845
2SC2631
2SC2632
2SC3940A
2SC945(A)

2SA1110
2SC2590

2SD1266

2SA933S
2SC1740S

2SA1535
2SC3944

TC4001BP

TC9130P

UPC1237HA


UPC7815HF

2SK163

UPC7915HF

DC
ter w
tions

EXPLODED VIEW (UNIT)



Parts with the exploded numbers larger than 700 are not supplied.

PARTS LIST

※ New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No.	Address	New Parts	Parts No.	Description	Destination	Remarks
参照番号	位置	新	部品番号	部品名 / 規格	仕向	備考
L-1000M						
1	1A	*	A52-0138-03	TOP PLATE ASSY		
2	2A	*	A20-5897-05	PANEL		
4	1B, 2C	*	A50-0334-03	SIDE PLATE ASSY		
-			B46-0092-03	WARRANTY CARD	K	
-			B46-0096-13	WARRANTY CARD	X	
-			B46-0121-03	WARRANTY CARD	P	
-			B46-0122-13	WARRANTY CARD	E	
-			B46-0143-13	WARRANTY CARD	T	
-		*	B50-9855-00	INSTRUCTION MANUAL (ENGLISH)		
-		*	B50-9856-00	INSTRUCTION MANUAL (FRENCH)	EP	
-		*	B50-9857-00	INSTRUCTION MANUAL (G,D,I)	E	
-			B58-0803-13	CAUTION CARD		
16	2B	*	C90-1782-15	ELECTROLYTIC CAPACITOR ASSY		
20	1C	*	D10-2355-05	LEVER		
23	1C		E03-0049-05	AC PLUG	T	
24	1C		E03-0041-05	AC OUTLET	KP	
24	1C		E03-0085-05	AC OUTLET	T	
25	1C		E30-0978-05	AC POWER CORD	KP	
25	1C		E30-1341-05	AC POWER CORD	X	
25	1C		E30-1416-05	AC POWER CORD	T	
25	1C	*	E30-2580-05	AC POWER CORD	E	
F1 ,2			F05-2525-05	FUSE (SEMKO) (250V T2.5A)	EXT	
F1 ,2			F06-5022-05	FUSE (UL) (250V 5A)	KP	
31	1B, 2C	*	G10-0155-04	NON-WOVEN FABRIC		
-		*	H01-8633-04	ITEM CARTON CASE		
-		*	H10-3892-02	POLYSTYRENE FOAMED FIXTURE (R)		
-		*	H10-3893-02	POLYSTYRENE FOAMED FIXTURE (L)		
-		*	H25-0232-04	PROTECTION BAG (235X350X0.03)		
-		*	H25-0383-04	PROTECTION BAG		
40	2B, 2C	*	J02-1055-05	FOOT		
41	1C		J41-0024-15	POWER CORD BUSHING	E	
41	1C		J42-0083-05	POWER CORD BUSHING	KPXT	
42	2B, 2C		J30-0270-04	SPACER		
43	1C	*	J32-0329-05	HEXAGON BOSS		
44	2B, 2C	*	J39-0154-04	SPACER		
45	2C		J11-0165-05	WIRE BAND		
-			J61-0307-05	WIRE BAND		
46	2A	*	K29-3779-04	KNOB POWER		
47	1C	*	K29-3824-04	KNOB LEVEL		
48	2A	*	K29-3853-04	KNOB ASSY SPEAKER		
52	2B	*	L01-8931-05	POWER TRANSFORMER	KP	
52	2B	*	L01-8932-05	POWER TRANSFORMER	E	
52	2B	*	L01-8937-05	POWER TRANSFORMER	XT	
53	1C	*	L92-0025-05	FERRITE CORE		
A	2A		N09-1445-05	SET SCREW (M3X8 ユラ)		
B	1C		N09-1648-05	MACHINE SCREW (M3X8 ハネツキナツキ)		
C	1B, 2C	*	N09-2707-05	DRESSED SCREW		
D	1B, 1C	*	N09-2767-05	SEMS (TAPTITE SCREW) (3X10 フレシ)		
E	2C	*	N09-2770-05	TAPTITE SCREW (3X8 ハイトツキ)		

E: Scandinavia & Europe K: USA P: Canada

U: PX(Far East, Hawaii) T: England M: Other Areas

UE: AAFES(Europe) X: Australia

⚠ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
F	2B	*	N09-2771-05	SEMS (TAPTITE SCREW) (4X8ハット)		
G	1B, 2C	*	N17-1040-45	TOOTHED LOCK WASHER		
H	1C		N30-3008-45	PAN HEAD MACHINE SCREW		
J	1A	*	N88-3006-45	FLAT HEAD TAPTITE SCREW		
K	2A		N89-2608-46	BINDING HEAD TAPTITE SCREW		
L	1A		N89-3006-45	BINDING HEAD TAPTITE SCREW		
M	1B, 2B		N89-3008-46	BINDING HEAD TAPTITE SCREW		
N	2A		N89-3010-45	BINDING HEAD TAPTITE SCREW		
P	2B, 2C		N89-3014-45	BINDING HEAD TAPTITE SCREW		
S	1A		N89-4016-46	BINDING HEAD TAPTITE SCREW		
T	1C		N29-0067-05	PUSH RIVET (3.5X4.5)	EX	
U	1C		N14-0123-05	NUT		
D101, 102			S15VB20	DIODE		
MAIN AMPLIFIER UNIT (X07-2502-70)						
C1 -4			CF92FV1H105J	MF 1.0UF J		
C5 -8			CF92FV1H221K	MF 220PF K		
C9 -12			C91-0654-05	CERAMIC 0.0012UF K		
C13 -16			CE04KW1H010M	ELECTRO 1.0UF 50WV		
C17 -20			CE04KW1E101M	ELECTRO 100UF 25WV		
C21 -24			C91-0664-05	CERAMIC 0.0033UF K		
C29 ,30			C90-1805-05	ELECTRO 330UF 25WV		
C31 ,32			CF92FV1H101K	MF 100PF K		
C33 -36			C91-1418-05	MICA 39PF K		
C37 -40			CF92FV1H151K	MF 150PF K		
C41 -44			C91-1420-05	MICA 56PF K		
C45 -48			CE04KW1C220M	ELECTRO 22UF 16WV		
C49 -56			CC45FSL1H221J	CERAMIC 220PF J		
C57 -64			CE04KW1H010M	ELECTRO 1.0UF 50WV		
C65 -68			CE04KW1H470M	ELECTRO 47UF 50WV		
C69 -72			CE04KW1H101M	ELECTRO 100UF 50WV		
C73 -76		*	C90-1806-05	ELECTRO 10UF 50WV		
C77 ,78			CE04KW1V470M	ELECTRO 47UF 35WV		
C79 -86			CF92FV1H221K	MF 220PF K		
L1 ,2			L40-1021-14	SMALL FIXED INDUCTOR(1.0MH,K)		
L3 -6			L40-1021-11	SMALL FIXED INDUCTOR(1.0MH,K)		
R5 -8		*	RN14BK2E5112FTS	RN 51.1K F 1/4W		
R37 ,38			RN14BK2E1961FTS	RN 1.96K F 1/4W		
R41 -48		*	RN14BK2E3482FTS	RN 34.8K F 1/4W		
R53 -56		*	RD14AB2E131JTS	FL-PROOF RD 130 J 1/4W		
R57 -60			RD14AB2E472JTS	FL-PROOF RD 4.7K J 1/4W		
R61 -76			RD14AB2E331JTS	FL-PROOF RD 330 J 1/4W		
R77 -84			RD14AB2E471JTS	FL-PROOF RD 470 J 1/4W		
R85 -92			RD14AB2E150JTS	FL-PROOF RD 15 J 1/4W		
R93 -100			RD14AB2E101JTS	FL-PROOF RD 100 J 1/4W		
R101-104			RD14AB2E122JTS	FL-PROOF RD 1.2K J 1/4W		
R105-108			RD14AB2E101JTS	FL-PROOF RD 100 J 1/4W		
D1 -6			HZS5.1S(B2)	ZENER DIODE		
D1 -6			RD5.1JS(B2)	ZENER DIODE		
D7 ,8			HSS104	DIODE		
D7 ,8			1SS133	DIODE		
D9 ,10			HZS15S(B)	ZENER DIODE		
D9 ,10			RD15JS(B)	ZENER DIODE		

E: Scandinavia & Europe K: USA P: Canada

U: PX(Far East, Hawaii) T: England M: Other Areas

UE: AAFES(Europe) X: Australia

△ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
D11 -30			HSS104	DIODE		
D11 -30			1SS133	DIODE		
D31 -34			MA27Q(A)	VARISTOR		
Q1 -16			2SA992(F,E)	TRANSISTOR		
Q17 -20			2SA733(A)(Q,P)	TRANSISTOR		
Q17 -20			2SA933S(Q,R)	TRANSISTOR		
Q21 -28			2SC1845(F,E)	TRANSISTOR		
Q29 -36			2SC2632(R,S)	TRANSISTOR		
Q37 -40			2SA1124(R,S)	TRANSISTOR		
Q41 -44			2SA1123(R,S)	TRANSISTOR		
Q45 -48			2SC2631(R,S)	TRANSISTOR		
Q49 -52			2SA1535(R,S)	TRANSISTOR		
Q53 -56			2SC3944(R,S)	TRANSISTOR		
Q57 ,58			2SA1110(R,S)	TRANSISTOR		
Q59 ,60			2SC2590(R,S)	TRANSISTOR		
AUDIO UNIT (X09-2942-70)						
C1 -4			CE04KW1H100M	ELECTRO 10UF 50WV		
C5 -12			CE04KW1H010M	ELECTRO 1.0UF 50WV		
C19 ,20			CF92FV1H104J	MF 0.10UF J		
C21 -24			CC45FSL1H331J	CERAMIC 330PF J		
C25 -30			CF92FV1H104J	MF 0.10UF J		
C31		*	C90-1798-05	ELECTRO 22UF 16WV		
C32		*	C90-1797-05	ELECTRO 22UF 10WV		
C33			CF92FV1H103J	MF 0.010UF J		
C34		*	C90-1799-05	ELECTRO 47UF 16WV		
C35			CE04KW1H4R7M	ELECTRO 4.7UF 50WV		
43	1B	*	J32-0329-05	HEXAGON BOSS		
H	1B		N89-3008-45	BINDING HEAD TAPTITE SCREW		
Q	1B		N09-0333-05	TAPPING SCREW (3X12, +ロツカフサ)		
R	1B		N35-3006-46	BINDING HEAD MACHINE SCREW		
S	1B	*	N89-4016-46	BINDING HEAD TAPTITE SCREW		
R9 -24			RD14AB2E4R7JTS	FL-PROOF RD 4.7 J 1/4W		
R25 -40			R92-0167-05	METAL-PLATE 0.22 K 5W		
R57 -64			RD14AB2E101JTS	FL-PROOF RD 100 J 1/4W		
R73 -76			RS14DB3D100JTE	FL-PROOF RS 10 J 2W		
R85			RS14DB3D561JTE	FL-PROOF RS 560 J 2W		
R86			RS14DB3D391JTE	FL-PROOF RS 390 J 2W		
VR1 -4			R12-1088-05	TRIMMING POT. (3.3K ヲテ)		
D1 ,2			S15VB20	DIODE		
D3 -11			HSS104A	DIODE		
D3 -11			1SS131	DIODE		
IC1			UPC1237HA	IC(POWER AMP)		
IC2			UPC7815HF	IC(VOLTAGE REGULATOR/ +15V)		
IC3			UPC7915HF	IC(VOLTAGE REGULATOR/ -15V)		
Q1 -4			2SC4137F19(V,W)	TRANSISTOR		
Q5 -12			2SD1718*5	TRANSISTOR		
Q13 -20			2SB1163*5	TRANSISTOR		
Q21 -24			2SC1845(F,E)	TRANSISTOR		
Q25 -28			2SA992(F,E)	TRANSISTOR		
Q29 -32			2SC1740S(Q,R)	TRANSISTOR		
Q29 -32			2SC945(A)(Q,P)	TRANSISTOR		
Q33			2SA992(F,E)	TRANSISTOR		

E: Scandinavia & Europe K: USA P: Canada

U: PX(Far East, Hawaii) T: England M: Other Areas

UE: AAFES(Europe) X: Australia

△ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕 向	Re- marks 備考
ACCESSORY UNIT (X13-6342-70: E, 0-11:K, P, 0-51:X, T)						
D16 -21 D22 -32		*	B30-1286-05 B30-1283-05	LED LED		
C1 -4 C5 ,6 C7 ,8 C9 ,10 C11 ,12			CF92FV1H121K CF92FV1H564J CF92FV1H121K CF92FV1H152J C91-0088-05	MF 120PF K MF 0.56UF J MF 120PF K MF 1500PF J POLYSTY 100PF K		
C13 ,14 C15 -18 C19 -22 C23 -34 C35 -38		*	CF92FV1H152J C90-1803-05 CF92FV1H103J CF92FV1H121K CF92FV1H473J	MF 1500PF J ELECTRO 22UF 35WV MF 0.010UF J MF 120PF K MF 0.047UF J		
C39 -46 C47 -50 C51 -56 C59 -62 C63 ,64			CF92FV1H102J CF92FV1H472J CF92FV1H221K CE04KW1E331M CF92FV1H102J	MF 1000PF J MF 4700PF J MF 220PF K ELECTRO 330UF 25WV MF 1000PF J		
C65 C66 C67 -69 C70 ,71 C72			CF92FV1H154J CF92FV1H334J CK45FF1H103Z C90-1332-05 CE04KW1V100M	MF 0.15UF J MF 0.33UF J CERAMIC 0.010UF Z NP-ELEC 10UF 25WV ELECTRO 10UF 35WV		
C73 C74 C75 -78 C79 ,80 C81			CE04KW1V4R7M CE04KW1E471M CK45FF1H103Z C91-0971-05 CE04KW1C470M	ELECTRO 4.7UF 35WV ELECTRO 470UF 25WV CERAMIC 0.010UF Z FILM 0.01UF 250WV ELECTRO 47UF 16WV		
C82 C83 -86 C87 C89 ,90			CE04KW1V100M CE04KW1E331M CE04KW1E470M CF92FV1H124J	ELECTRO 10UF 35WV ELECTRO 330UF 25WV ELECTRO 47UF 25WV MF 0.12UF J		
E1 ,2 E3 ,4 E5		*	E06-0305-05 E20-0477-05 E13-0253-05	CYLINDRICAL RECEPTACLE BALANCE SCREW TERMINAL BOARD(4P)SP OUT PHONE JACK (2P) UNBALANCE		
57 57	1B,2B 1B,2B		J13-0041-05 J13-0054-05	FUSE CLIP FUSE CLIP	KP EXT	
L1 -6 L11 -14 L15 -20 L25 ,26 T1			L40-1011-47 L39-0188-05 L40-1021-14 L40-1021-14 L01-7651-05	SMALL FIXED INDUCTOR(100UH,K) PHASE-COMPENSATION COIL SMALL FIXED INDUCTOR(1.0MH,K) SMALL FIXED INDUCTOR(1.0MH,K) POWER TRANSFORMER	KP	
T1 T1			L01-7652-05 L01-7657-05	POWER TRANSFORMER POWER TRANSFORMER	E XT	
E	1C	*	N09-2770-05	TAPTITE SCREW (3X8)		
R9 -12 R25 -28 R29 -32 R35 R41 -44 R45 -48		*	RN14BK2E2371FTS RD14AB2E4R7JTS RS14DB3D100JTE RS14DB3A392JTE RS14DB3D471JTE RS14DB3A272JTE	RN 2.37K F 1/4W FL-PROOF RD 4.7 J 1/4W FL-PROOF RS 10 J 2W FL-PROOF RS 3.9K J 1W FL-PROOF RS 470 J 2W FL-PROOF RS 2.7K J 1W		

E: Scandinavia & Europe K: USA P: Canada
 U: PX(Far East, Hawaii) T: England M: Other Areas
 UE: AAFES(Europe) X: Australia

⚠ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕 向	Re- marks 備考
R77 VR1 ,2		*	RS14DB3A471JTE R10-4034-05	FL-PROOF RS 470 J 1W POTENTIOMETER		
K1 -4 K5 -8 K11 S1 S2 -4			S51-2089-05 S51-2045-05 S51-1036-05 S31-2094-05 S40-1064-05	MAGNETIC RELAY MAGNETIC RELAY MAGNETIC RELAY SLIDE SWITCH PUSH SWITCH		
D1 -4 D1 -4 D5 -8 D5 -8 D11			HZS11N(B) RD11ES(B) HZS24N(B) RD24ES(B) HSS104	ZENER DIODE ZENER DIODE ZENER DIODE ZENER DIODE DIODE		
D11 D12 ,13 D12 ,13 D14 ,15 D14 ,15		*	1SS133 HZS5.1JS(B2) RD5.1JS(B2) HSS104 1SS133	DIODE ZENER DIODE ZENER DIODE DIODE DIODE		
D33 D33 D34 D34 D35			HSS104 1SS133 HZS10N(B) RD10ES(B) HSS104A	DIODE DIODE ZENER DIODE ZENER DIODE DIODE		
D35 D36 -39 D40 D40 D41 -43			1SS131 S5566B HZS10N(B) RD10ES(B) HSS104A	DIODE DIODE ZENER DIODE ZENER DIODE DIODE		
D41 -43 IC1 ,2 IC3 IC4 Q1 -4		*	1SS131 NJM4580D-D TC4001BP TC9130P 2SC1740S(Q,R)	DIODE IC IC(NOR X6) IC(4CH IND CYCLIC TOUCH SWITCH) TRANSISTOR		
Q1 -4 Q5 Q5 Q6 Q6			2SC945(A)(Q,P) 2SA733(A)(Q,P) 2SA933S(Q,R) 2SC1740S(Q,R) 2SC945(A)(Q,P)	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q7 Q7 Q8 Q8 Q9			2SA733(A)(Q,P) 2SA933S(Q,R) 2SC1740S(Q,R) 2SC945(A)(Q,P) 2SD1266	TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR TRANSISTOR		
Q10 Q11 Q11 Q12 Q13 -15			2SK163(L) 2SA733(A)(Q,P) 2SA933S(Q,R) 2SK163(N) 2SC1740S(Q,R)	FET TRANSISTOR TRANSISTOR FET TRANSISTOR		
Q13 -15 Q16 Q17 -20			2SC945(A)(Q,P) 2SA1534A(R,S) 2SC3940A(R,S)	TRANSISTOR TRANSISTOR TRANSISTOR		

E: Scandinavia & Europe K: USA P: Canada
 U: PX(Far East, Hawaii) T: England M: Other Areas
 UE: AAFES(Europe) X: Australia

⚠ indicates safety critical components.

L-1000M

SPECIFICATIONS

Continuous Power Output

130 watts* per channel minimum RMS, both channels driven, at 8 Ω from 20 Hz to 20,000 Hz with no more than 0.006% total harmonic distortion.

150 W+150 W (1 kHz, 0.006%, 8 Ω)
155 W+155 W (DIN, 8 Ω , 1 kHz)
220 W+220 W (DIN, 4 Ω , 1 kHz)
200 W+200 W (EIA, 6 Ω)

Dynamic Power .. 178 W (8 Ω), 260 W (4 Ω), 330 W (2 Ω)

Total Harmonic Distortion ... 0.006% (20 Hz~20,000 Hz, 130 W, 8 Ω)
0.0004%
(1 kHz, 130 W, 8 Ω)

Input Sensitivity/Impedance

UNBALANCED 1.0 V/47 k Ω

BALANCED 2.0 V/50 k Ω

Frequency Response .. 5 Hz~100,000 Hz, +0 dB, -3 dB

Signal to Noise Ratio

UNBALANCED 115 dB (IHF'66)/95 dB

BALANCED 125 dB (IHF'66)/101 dB

Damping Factor 130 (50 Hz)

General

Power Consumption 7 A (U.S.A. and Canada)
500 W (Others)

Dimensions W: 440 mm (17-3/8")
H: 166 mm (6-9/16")
D: 446 mm (17-9/16")

Weight (Net) 27.0 kg (59.5 lb)

* Measured pursuant to Federal Trade Commission's Trade Regulation rule on Power Output Claims for Amplifier in U.S.A.

KENWOOD follows a policy of continuous advancements in development. For this reason specifications may be changed without notice. DOLBY and the double-D symbol are trademarks of Dolby Laboratories Licensing Corporation. Noise reduction circuit made under license from Dolby Laboratories Licensing Corporation.

KENWOOD poursuit une politique de progrès constants en ce qui concerne le développement. Pour cette raison, les spécifications sont sujettes à modifications sans préavis. La marque DOLBY et le double "D" sont des marques déposées des Dolby Laboratories. Le système de réduction du bruit de fond est fabriqué sous licence des Dolby Laboratories.

KENWOOD strebt ständige Verbesserungen in der Entwicklung an. Daher bleiben Änderungen der technischen Daten jederzeit vorbehalten. DOLBY und Doppel-D-Symbol sind eingetragene Warenzeichen der Dolby Laboratories. Dolby-Rauschunterdrückung mit Lizenz der Dolby Laboratories gefertigt.

Note:

Component and circuitry are subject to modification to insure best operation under differing local conditions. This manual is based on the Europe (E) standard, and provides information on regional circuit modification through use of alternate schematic diagrams, and information on regional component variations through use of parts list.

KENWOOD CORPORATION

Shionogi Shibuya Building, 17-5, 2-chome Shibuya, Shibuya-ku, Tokyo 150, Japan

KENWOOD U.S.A. CORPORATION
2201 East Dominguez Street, Long Beach, CA 90810;
550 Clark Drive, Mount Olive, NJ 07828, U.S.A.

KENWOOD ELECTRONICS CANADA INC.
P.O. BOX 1075, 959 Gana Court, Mississauga, Ontario, Canada L4T 4C2

TRIO-KENWOOD U.K. LIMITED
KENWOOD House, Dwight Road, Watford, Herts., WD1 8EB United Kingdom

KENWOOD ELECTRONICS BENELUX N.V.
Mechelsesteenweg 418 B-1930 Zaventem, Belgium

KENWOOD ELECTRONICS DEUTSCHLAND GMBH
Rembrücker-Str. 15, 6056 Heusenstamm, West Germany

TRIO-KENWOOD FRANCE S.A.
13 Boulevard Ney, 75018 Paris, France

KENWOOD LINEAR S.p.A.

20125, MILANO-VIA ARBE, 50, ITALY
KENWOOD ELECTRONICS AUSTRALIA PTY. LTD. (INCORPORATED IN N.S.W.)
4E Woodcock Place, Lane Cove, N.S.W. 2066, Australia

KENWOOD & LEE ELECTRONICS, LTD.
Wang Kee Building, 4th Floor, 34-37, Connaught Road, Central, Hong Kong